

Basic-Commands

device to value [S7]

System-Mode:	0,99
Command:	[S7.Adress.Value.fading]
Answer:	[S7.0x_Port.0x_Adress_h.0x_Adress_l.0x_Value] optional

load scene [F2]

System-Mode:	0,99
Command:	[F2.Scene.fading]
Answer:	[F2.0x_Scene.“OK”]

group with scene [G3]

System-Mode:	0,99
Command:	[G3.Group.Scene.fading]
Answer:	[G3.0x_Group.0x_Scene.“OK”]

group with value [G4]

System-Mode:	0,99
Command:	[G4.Group.Value.fading]
Answer:	[G4.02x_Group.02x_Value.“OK”]

sequencer start/stop [H1]

System-Mode:	0,99
Command:	[H1.Sequenz.Aktiv]
Answer:	[H1_2.0x_sequenz.0x_aktiv.OK]
Answer:	[H1_3.0x_sequenz.0x_aktiv.Error]
Answer:	[H1_4.0x_sequenz.0x_aktiv.OK]
Answer:	[H1_5.0x_sequenz.0x_aktiv.Error]

MediaEngine start/stop [M1]

System-Mode:	0,2,99
Command:	[M1.Effect.Aktiv]
Answer:	[M1.0x_effect.0x_aktiv.OK]

From:

<https://api.intelligent-lighting.de/> - **Netcomposer API**

Permanent link:

<https://api.intelligent-lighting.de/doku.php?id=simple:basic-commands>

Last update: **2016/07/25 15:42**

